

ANN6L (6-zone Annunciator)

Product Specification



DESCRIPTION

Usually mounted at the nursing station, reception, or guard station, the ANN6L is the central alarm panel that monitors the status of up to 6 alarm zones. Each additional ANN6L will allow six more zones to be monitored. The reset switches can be set so that only one reset switch needs to be pressed in order to reset all the panels. Up to 6 ANN6L units can be used. Alarms can also be monitored at separate locations with additional ANN6L panels that provide either common or local alarm status. Reset can be performed on any ANN6L when used for common alarm indicators.

FEATURES

- Flat lexan with raised membrane switches provides an easy-to-clean surface
- 6-zone annunciator
- 6 bi-color LED's indicate alarm priority: Red = Latching / Yellow = Non-Latching
- Two distinctive piezo alarms indicate alarm priority; may be disabled during install
- Latching and non-latching alarms
- Alarm inputs accepted via N/O or N/C dry contacts or a voltage transition (switch selected functions)
- Reset function can be ganged with other annunciator resets for remote operation
- Silence button deactivates audible alarm; new alarms activate audible alarm
- Onboard Form C relay for auxiliary output
- Mounts in a standard 2 gang electrical box (supplied)
- External speaker output provided

SPECIFICATIONS

Order Information

Model	Annunciator Panel (ANN6L)
Part Number	AGEAN01-060

General

Input Voltage	12 or 24 VDC @ 100 mA max
Alarm Zones	6 (expandable by adding multiple ANN6L's)

Physical

Size	4.5 x 4.5 x 3" (11.4 x 11.4 x 7.6 cm)
Mounting	2 gang standard electrical box
Cable Length (Power 18 AWG)	328 ft. (100 M)
Cable Length (Single 22 AWG)	328 ft. (100 M)

Warranty

2 years